

# JVC<sup>®</sup>

The Perfect Experience / —  
/

## FS-GD7

### DVD Micro Component System



**DVD**  
AUDIO/VIDEO™

**5-DISC**  
TRAY CHANGER

JVC's 5-Disc DVD Micro Component Systems are the perfect addition to any room with it's stylish looks and full array of features for your listening enjoyment.

## Product Description

High-power 5-DVD changer system with USB input (PC Link) -- featuring DVD-Audio playback, Progressive Scan Output, Clear Voice Function, and Sound Turbo II

## Basic Features

- Sources: DVD-Audio/Video, DVD-R/RW (Video Format), CD, CD-R/RW, SVCD/VCD, MP3/JPEG Digital Still (CD-R/RW), Tuner
- Power Output: 90 watts per channel\*
- 2-Way Bass-Reflex: 4-3/4" (12cm) Cone Woofer, 1-5/8" (4cm) Cone Tweeter
- Display Dimmer
- COMPU PLAY for one touch playback
- Sleep Timer
- Wake-up Volume
- Electronic Bass/Treble Tone Controls
- Program (99 tracks) / Random / Repeat Play

\* min. RMS, driven into 6 ohms, at 1kHz, with no more than 10% total harmonic distortion (FTC)

## Convenience Features

- DVD-Audio high-quality sound playback
- 5-disc changer for non-stop audio/visual entertainment
- Dolby Digital/DTS Decoder (2ch)
- Digital Direct Progressive Scan Output for smooth high-resolution pictures
- DVD Express Play Start shows the first scene quickly
- 192kHz/24-bit Audio D/A Converter for reproduction of high quality audio
- 12-bit/108MHz Video D/A Converter
- Clear Voice Function
- USB input for receiving audio signals direct from PCs (PC Link)
- 3-Preset Timer
- 2-Way Bass-Reflex Speakers
- Active Hyper-Bass PRO
- 3D-PHONIC
- Sound Turbo II boosts sound excitement with two modes suited for movies or music
- Front AUX Input

## General Specifications

### DVD Player:

- Playable Formats: DVD-Audio/Video, DVD-R/RW (Video Format), CD, CD-R/RW, SVCD/VCD, MP3/JPEG Digital Still (CD-R/RW)
- Slow/Zoom/Angle/Time/Search/Still/Resume
- Dolby Digital/DTS Decoder (2ch)

- Digital Direct Progressive Scan Output
- DVD Express Play Start
- Rolling Pickup
- 192kHz/24-bit Audio D/A Converter
- 12-bit/108MHz Video D/A Converter
- Number of Programs - 99
- Program/Random/Repeat Play
- On-Screen Language (English/French/Spanish)
- Optical Digital Output (Dolby Digital/DTS Digital Out)
- Horizontal Resolution - 500 Lines

### Amplifier/Tuner:

- 90 watts per channel, min. RMS, driven into 6 ohms, at 1kHz, with no more than 10% total harmonic distortion
- AM/FM Digital Tuner
- Number of Presets(30FM and 15AM)
- Active Hyper Bass PRO
- Electronic Bass/ Treble Tone Controls
- Sound Turbo Ver. II
- 3D PHONIC

### Terminals:

- Audio Out: Optical & Subwoofer
- Video Out: Component, S-Video, Composite
- USB Input
- Audio In (Analog): Front AUX
- Headphone Out

### General:

- Clear Voice Function
- Rotary Encoder Volume Control
- Display Dimmer
- COMPU PLAY
- Clock/3-Preset Timer
- Sleep Timer
- Wake-Up Volume

### Speakers:

- 2-Way, Bass-Reflex
- Woofer (or Full Range) 4 3/4 (12cm),Cone
- Tweeter 1 5/8 (4cm),Cone
- Detachable Grilles
- Magnetically Shielded

## Details, Weights & Measurements

### Center Unit:

Dimensions (WxHxD) inches: 7 1/2 x 8 7/8 x 16  
Approximate Weight (lbs./kg.): 14.4/6.5

### Speakers:

Dimensions (WxHxD) inches: 6 1/2 x 11 5/16 x 9 3/8  
Approximate Weight (lbs./kg.): 6.2/2.8



DISTRIBUTED BY

**JVC COMPANY OF AMERICA**  
A Division of JVC Americas Corp.  
1700 Valley Road, Wayne, NJ 07470  
CONSUMER INFORMATION CENTER 1-800-252-5722  
www.jvc.com

"JVC" is the trademark of Victor Company of Japan, Limited.