

www.jvc.com



UX-G210 Key Features

CD Micro Component System featuring USB Host, Front Audio Input, MP3/WMA Playback, and 1-bit DA Converter.

Product Highlights

- :: USB Host (2.0 Full Speed)
- :: Front Audio Input
- :: 1-bit DA Converter
- :: Hyber-Bass Sound
- :: 4 Sound Modes (ROCK/POP/CLASSIC/JAZZ)
- :: Rotary Encoder Volume Control
- :: Plays MP3/WMA (CD-R/RW, USB) with ID3 Tags
- :: 10 Watt Total Power
- :: Digital Tuner
- :: 3-15/16" (10cm) Full-Range Speakers
- :: Clock/Timer
- :: Bass/Treble Tone Control

Details, Weights & Measures

CENTER UNIT

Dimensions (WxHxD) in.: $5^{15}/_{16} \times 6^{15}/_{16} \times 8^{5}/_{16}$

Weight: 4.7 lbs

SPEAKERS

Dimensions (WxHxD) in.: $5^{9}/_{16} \times 6^{13}/_{16} \times 6^{3}/_{4}$

Weight: 2.7 lbs

Specifications are subject to change without notice.

Specifications

| AMPLIFIER/TUNER | |
|-------------------------------|---------------------------------|
| Power Output (with 10% THD) | 10W |
| Hyper-Bass Sound | ΙΟΨ |
| Sound Modes | 4 Mades (POCV/POD/CLASSIC/JA77) |
| Tuner Preset Stations | 4 Modes (ROCK/POP/CLASSIC/JAZZ) |
| | 20 FM |
| CD PLAYER | |
| Playable Formats | |
| CD/CD-R/RW | |
| MP3 with ID3 Tag | (CD-R/RW, USB) |
| WMA with WMA Tag | (CD-R/RW, USB) |
| Mechanism Type | 1-CD Tray |
| 1-bit D/A Converter | |
| Number of Programs | 32 |
| Program/Random/Repeat Play | |
| Dynamic Range (1kHz) | 60dB |
| Signal-to-Noise Ratio | 60dB |
| ΓERMINALS | |
| Analog | Front |
| Headphone Out | Rear |
| USB Host (2.0 Full-Speed) | Front |
| JSB Host | |
| Playable Formats | MP3,WMA |
| Repeat/Random | |
| Program Play | 32 |
| Power Supply | |
| GENERAL | |
| Rotary Encoder Volume Control | |
| CD Display | |
| Sleep Timer | |
| Remote Control | (Card Type) |
| SPEAKERS | (cara type) |
| Type | Full-Range, Bass-Reflex |
| Woofer | 3-5/16" (10cm), Cone |
| Impedance | 4 ohms |
| · | 4 011113 |
| Fixed Grilles | |
| | |
| | |
| | |
| | |
| | |
| | |
| | |
| | |
| | |
| | |

Specifications are subject to change without notice.

