

Made for iPhone

USB/CD Receiver with Front AUX















































## **Key Benefits**

By connection to 1A USB, JVC Music Control app allows easy song browsing from Android<sup>™</sup>, while USB memory becomes your playlist library with JVC Playlist Creator software. Enjoy Pandora from your iPhone<sup>®</sup>, with not only control, but thumbs-up/down also available from the headunit. MOS-FET power amp and 24-bit DAC provide quality sound. Other features include front AUX input, 3-band parametric iEQ, and Radio Timer. Bluetooth<sup>®</sup> Wireless Technology is also available with an optional adapter.



#### **\***Pandora Control

Listen to Pandora Radio from your iPod/iPhone app via USB connection, with station names etc. displayed on the panel. Thumbs-up/down, forward skip, pause/play, and search station/bookmark can all be controlled using the keys on the headunit.





 $\begin{bmatrix} PANDORA^{\!\otimes} \end{bmatrix}$ 



#### **\*Ready for Bluetooth® Adapter (KS-BTA100)**

With the optional KS-BTA100 adapter, you can enjoy the safety and convenience of Bluetooth® Wireless Technology such as hands-free calling, voice dialing, and audio streaming. The compact all-in-one adapter has microphone/keys/LED functions, and can be easily connected via the AUX.



Hands-Free Calls - Voice Dialing

Redial Call Private Mode Audio Streaming Noise/Echo Cancellation



### **\*Separated Brightness Control (32 steps)**

With JVC's CD receivers, you can easily control the brightness separately for left and right in 32 steps, for increased safety or to suit the car environment.

#### **\*Auto Dimmer**

Day and night memory settings available for auto dimmer.



### **\*Apps Control for iPod Mode**

Song information display and certain control features are available on the headunit for some apps, when the app is launched during iPod Mode.



# **\*JVC Original Apps/Software for Smartphone/Devices**



#### JVC Music Control (for Android™)\*

\* Smartphones with Android™ 2.2 and above.

JVC Music Control is a free download app that allows Android users to listen to favorite songs through an iPod like browsing experience via USB



Mass Storage Mode. Browse music by Artist, Album or Song Title through the headunit. Also generates playlists based on a particular Mood, much like a personal DJ.

## **JVC Playlist Creator**

Use PC software (for Windows®) to create a Playlist of tunes on USB memory which can be used in your car.



#### \*1A USB Audio for iPod/iPhone and Smartphones

Connect your iPod/iPhone or other smartphones to the unit's 1A USB port, and enjoy music in clear, digital sound with full-speed transfer. Your device's battery will be charged

during connection.



## \*Easy/Pro EQ Setting (3-Band Parametric iEQ)

Adjusts the center frequency, bandwidth and levels at each of 2 bands. Plus 5 initial and 1 user EQ presets. With Pro mode, the EQ can customize the sound for your ears. A separate setting for the subwoofer level is also available.

| <b>Control Range</b> | Bass:      | 60Hz,         | 80Hz, | 100Hz,  | 200Hz  |   |
|----------------------|------------|---------------|-------|---------|--------|---|
|                      | Mid-range: | 500Hz,        | 1kHz, | 1.5kHz, | 2.5kHz | Ī |
| Bass/Middle Level    |            | -6 - +6 level |       |         | Ī      |   |
| Q (Band with)        |            | 0.75~2.       | 0Q    |         |        | Ī |

| Initial Presets                |
|--------------------------------|
| <ul> <li>DYNAMIC</li> </ul>    |
| <ul> <li>FLAT</li> </ul>       |
| <ul> <li>NATURAL</li> </ul>    |
| <ul> <li>VOCAL BOOS</li> </ul> |
| <ul> <li>BASS BOOST</li> </ul> |

#### **★ Detachable Face**

With JVC headunits, you can easily remove the control panel and take it with you for security.

#### **Key Specifications** Maximum Power Output 50W × 4 LPF (Subwoofer) off/55/85/120Hz/Through (-12dB/oct) Line Pre-Output Terminals 1 (Rear/Subwoofer Selectable) Subwoofer Output with Level/Frequency Control 2.5V Line Output Level Subwoofer Output Level 2.5V -15dB - +15dB Subwoofer Gain Control Load Impedance $4\Omega$ (4 - $8\Omega$ allowable) Line Output Impedance ≤ 600Ω

| Dimensions (W × H × D) |                             |  |
|------------------------|-----------------------------|--|
| Installation Size      | 7 3/16" × 2 1/18" × 6 5/16" | 181.7 × 52.7 × 159 mm                    |
| Panel Size             | 7 7/16" × 2 3/8" × 9/16"    | $188 \times 58.5 \times 12.6 \text{ mm}$ |
| Detachable Face Plate  | 6 3/4" × 1 13/16" × 7/8"    | 169 8 × 46 4 × 22 mm                     |

